



Wireless, Boosted

The AmpliFi MeshPoint features an adjustable Super Antenna and fits discreetly in any household, wherever dead spots need coverage. Add MeshPoints as needed to an AmpliFi network or turn an ordinary router into a powerful mesh network. Signal strength LEDs are integrated into the design to ensure the system is positioned for optimal performance.

MeshPoint Specifications

| | |
|-----------------------|-------------------------------------------|
| Dimensions | 243.83 x 54 x 57.75 (9.60 x 2.13 x 2.27") |
| Weight | 224 g (7.90 oz) |
| Max. TX Power | 26 dBm |
| Radios | 2 |
| MIMO Chains | 6 |
| Speed | 1750 Mbps |
| ESD/EMP Protection | ± 24kV Air/Contact |
| Buttons | Reset |
| Antennas | (1) Dual-Band Antenna, Tri-Polarity |
| Wi-Fi Standards | 802.11ac |
| Power Save | Supported |
| Wireless Security | WPA2-PSK AES/TKIP |
| Operating Temperature | 14 to 131° F (-10 to 55° C) |
| Operating Humidity | 5 to 95% Noncondensing |
| Certifications | FCC / CE / IC |

Supported Data Rates

| | |
|----------|--------------------------------------------------|
| 802.11ac | 13 Mbps to 1300 Mbps (MCS0 - MCS9, VHT 20/40/80) |
| 802.11n | 6.5 Mbps to 450 Mbps (MCS0 - MCS23, HT 20/40) |
| 802.11a | 6, 9, 12, 18, 24, 36, 48, 54 Mbps |
| 802.11b | 1, 2, 5.5, 11 Mbps |
| 802.11g | 6, 9, 12, 18, 24, 36, 48, 54 Mbps |

Your Wi-Fi Router is No Longer Something to Hide

Designed from the outside in, AmpliFi is meant to be a showcase piece for the modern home.



Perfected User Experience

The intuitive AmpliFi app allows instant setup, configuration, powerful reporting metrics, parental controls, remote access, and easy guest access. The mobile app is available for download on Android and iOS smartphones.





Guest Access Simplified

AmpliFi utilizes an *open time window* concept to allow instant guest access without the security compromise and inconvenience of password sharing.



24/7 Live Global Chat Support

24/7 Live Global Chat Support within the AmpliFi app and also online at help.amplifi.com



Specifications are subject to change. Ubiquiti products are sold with a limited warranty described at: www.ubnt.com/support/warranty
©2018 Ubiquiti Networks, Inc. All rights reserved. Ubiquiti, Ubiquiti Networks, the Ubiquiti U logo, ULabs, the ULabs logo, AmpliFi, and Home Wi-Fi Mesh Technology are trademarks or registered trademarks of Ubiquiti Networks, Inc. in the United States and in other countries. Apple, the Apple logo, and iPhone are trademarks of Apple Inc., registered in the U.S. and other countries. App Store is a service mark of Apple Inc. Android, Google, Google Play, the Google Play logo and other marks are trademarks of Google Inc. All other trademarks are the property of their respective owners.



www.amplifi.com